

## AMPERE-HOUR METER AHCO-60

The AHCO-60 is designed to accurately measure power consumption or power generation by recording DC current on a 4-digit mechanical display.

### FEATURES

Measures power consumption of battery operated systems.

Measures power generation by photovoltaic, wind or wave generator installations.

Current range 1-100 amps.

Mechanical display retains reading in the event of power failure.

Reverse polarity protection.

Polycarbonate enclosure.



### SPECIFICATIONS

<b>Voltage:</b>	10-32 volt
<b>Power consumption:</b>	Max 0.3mA @ no load Max 0.6mA @ rated load
<b>Voltage drop:</b>	60m V @ rated load
<b>Accuracy:</b>	± 2%
<b>Current range:</b>	0-1 or 10A. Extended to 100A using external shunts
<b>Operating temperature:</b>	-20°C to +60°C
<b>Dimensions:</b>	120 x 80 x 95mm (H x W x D)
<b>Weight:</b>	380g

**Pharos Marine**  **Automatic Power**

AB Pharos Marine Ltd, Steyning Way, Hounslow, Middlesex, TW4 6DL, England Tel: 44-20-8538 1100, Telefax: 44-20-8577 4170

Website: [www.pharosmarine.com](http://www.pharosmarine.com) Email: [sales@pharosmarine.com](mailto:sales@pharosmarine.com)

Automatic Power Inc., P.O Box 23078, Houston, Texas 77223-0738, U.S.A Tel: 1 (713) 228-5208, Telefax: 1 (713) 228-3717

AB Pharos Marine Pte Ltd., 35 Tannery Road, #05-05, Tannery Block, Ruby Industrial Complex, Singapore 347740 Tel: (65) 6747-9325, Telex: RS 33272 PHAROS, Telefax: (65) 6746-0478